

100A BATTERY CHARGER

Part Number	Input Power	Rated Output Current / Duty Cycle	Input Current at Rated Output	Charging Voltages	Dimensions (H X W X D)	Shipping Weight	Agency
K3153-1	120/1/60	15A (6,12V) / 2A (12V) 100A (12V, 3 sec. on, 400 off)	2.7A (18.8A Start)	6 & 12 volt	Ctn: 7½" X 11½" X 9¾" Unit: 5½" X 9¾" X 8"	14 lbs.	cULus

6 & 12 V, 15 Amp Manual & Automatic Battery Charger with 100 amp 12V Engine Start

FEATURES

- **100 amp engine start** helps start stubborn 12V motors.
- **15 amp high, 2 amp low 12V** Automatic and Manual charge settings.
- **15 amp high 6V** Manual charge setting.
- **Automatic 12V Deep Cycle setting** for full charge.
- **12V Manual settings** allow charging deeply discharged 12V batteries that many automatic chargers cannot.
- **12V Automatically shuts off** when battery is fully charged. Resumes charging if battery becomes discharged.
- **Charges 6 & 12 volt** maintenance free, conventional wet, deep cycle, AGM, and gel batteries used in cars, trucks, farm equipment, RV, boats and commercial applications.
- **Charges automotive batteries in 2 to 4 hours.**
- **Low 2 amp setting** is ideal for charging 12 volt motorcycle and lawn mower batteries.
- **Rotary Switch** simplifies charge/start selection.
- **LEDs** - reverse connection and abnormal battery red light, charging and charge complete green light.
- **Heavy duty insulated clamps** grip securely on all batteries.
- **Six-foot copper output cables.**



APPLICATIONS



100A BATTERY CHARGER

CENTURY Battery Charger
Chargeur de batterie
Cargador de batería

1 BATTERY / BATTERIES / BATERÍA
100% 0%
AMPS / A
0 2 5 7 9 12 15

2 **100A** 12V ENGINE START
DÉMARRAGE MOTEUR 12V
ARRANQUE DEL MOTOR 12V

15A 6/12V HIGH RATE CHARGE
CHARGE À HAUTE INTENSITÉ 6/12V
CARGA RÁPIDA 6/12V

2A 12V LOW RATE CHARGE
CHARGE DE BASSE INTENSITÉ 12V
BAJA TASA DE CARGA 12V

3 Automatic / Automatique / Automático
OFF/ARRÊT / APAGADO

4 Manual / Manuel

5 100A 12V START/DÉMARRER / COMENZAR

6 15A 12V, 2A 12V, 15A 6V, 15A 12V

7 CHARGED / CHARGÉ / CARGO
Green light for AUTOMATIC only.
Lumière verte pour automatique seulement
Luz verde para el automático solo

8 REVERSE / REVERSE / REVERSE / REVERSE
Abnormal / Anormal

Model: K3153-1

CAUTION: Read warning information on back panel and instruction manual before operating.
ATTENTION: Lire les mises en garde au verso et le manuel de fonctionnement, avant d'opérer.
CUIDADO: Lea la información de advertencia en la parte posterior del manual de instrucciones antes de hacer cualquier operación.

- 1. Ammeter for showing rate of charge.
- 2. Automatic charge setting for Deep Cycle type batteries.
- 3. Automatic setting will turn off when battery is fully charged and resumes if discharged.
- 4. Manual setting for charging discharged batteries.
- 5. 100A of additional starting power for those cold mornings.
- 6. 2A setting for motorcycle and lawnmower batteries.
- 7. Full charge indicator.
- 8. Reverse connection indicator.

UNIT UPC CODE

